

Catalog for Perkins Series Diesel Generator

Powered by Perkins engine, it enjoys high stability, reliability, durability and long life with a wide range of power output(7-1800kW). It is widely used in the area of communication, industry, projects, mining, rescuing, military and so on. The series of 400, 1100, 1300, 2000, 4000 diesel engines are manufactured by UK Perkins or its Subordinate factory according to global quality standards. The global service net of Perkins can provide our customers with reliable and guaranteed service.

Gen-set Model	Prime Power		Standby Power		Engine	Alternator		
	kVA	kW	kVA	kW	Perkins	Stamford	Leroysoner	Mecc Alte
DP0007S	9	7	10	7.7	403D-11G	PI 044E	LSA 40 VS1	ECO28-2VS/4
DP0010S	13	10	14	11	403D-15G	PI 044F	LSA 40 VS2	ECO28-0S/4
DP0016S	20	16	22	17.6	404D-22G	PI144D	LSA 40 M5	ECO28-1LN/4
DP0024S	30	24	33	26.4	1103A-33G	PI 144G	LSA 42.2 L9	ECO28-VL/4
DP0036S	45	36	50	39.6	1103A-33TG1	UCI 224D	LSA 43.2 S25	ECO32-3S/4
DP0048S	60	48	66	52.8	1103A-33TG2	UCI 224E	LSA 43.2 M45	ECO32-2L/4
DP0052S	65	52	72	57.2	1104A-44TG1	UCI 224F	LSA 43.2 L65	ECO32-3L/4
DP0064S	80	64	88	70.4	1104A-44TG2	UCI 224G	LSA 43.2 L8	ECP34-1S/4
DP0075S	94	75	103	82.5	1006TG1A	UCI 274C	LSA 44.2 VS4	ECP34-2S/4
DP0080S	100	80	110	88	1004C-44TAG2	UCI 274C	LSA 44.2 VS4	ECP34-2S/4
DP0108S	135	108	149	118.8	1006TAG	UCI 274E	LSA 44.2 S75	ECP34-2L/4
DP0120S	150	120	165	132	1006TAG2	UCI 274F	LSA 44.2 M95	ECP34-2L/4
DP0145S	181	145	199	159.5	1106C-E66TAG4	UCI 274G	LSA 46.2 M3	ECO38-1SN
DP0160S	200	160	220	176	1306C-E87TAG3	UCI 274H	LSA 46.2 M5	ECO38-2SN
DP0182S	228	182	250	200.2	1306C-E87TAG4	UCD 274J	LSA 46.2 L6	ECO38-3SN
DP0200S	250	200	275	220	1306C-E87TAG6	UCD 274K	LSA 46.2 L6	ECO38-1LN
DP0280S	350	280	385	308	2206C-E13TAG2	HCI 444E	LSA 47.2 VS1	ECO38-3LN
DP0320S	400	320	440	352	2206C-E13TAG3	HCI 444F	LSA 47.2 S4	ECO40-1S
DP0364S	455	364	501	400.4	2506A-E15TAG1	HCI 544C	LSA 47.2 S5	ECO40-2S
DP0400S	500	400	550	440	2506A-E15TAG2	HCI 544C	LSA 47.2 M7	ECO40-3S
DP0440S	550	440	605	484	2806C-E18TAG1A	HCI 544E	LSA 47.2 L9	ECO40-1.5L

Gen-set Model	Prime Power		Standby Power		Engine	Alternator		
	kVA	kW	kVA	kW	Perkins	Stamford	Leroysoner	Mecc Alte
DP0480S	600	480	660	528	2806A-E18TAG1A	HCI 544E	LSA 47.2 L9	ECO40-1.5L
DP0520S	650	520	715	572	2806A-E18TAG2	HCI 544F	LSA 49.1 S4	ECO40-2L
DP0580S	725	580	798	638	4006-23TAG2A	LVI 634B	LSA 49.1 M6	Note: 1. bridge fuel tank (power under 520kW) 2. Deepsea controller(standard) 3. supply scope: diesel generator, controller, battery, battery connecting wire, exhaust pipe, flange, shock absorber, muffler, elbow, tools, documents etc
DP0640S	800	640	880	704	4006-23TAG3A	HCI 634G	LSA 49.1 M75	
DP0675S	844	675	928	742.5	4008TWG2	HCI 634H	LSA 49.1 L9	
DP0724S	905	724	996	796.4	4008TAG1A	HCI 634H	LSA 49.1 L10	
DP0800S	1000	800	1100	880	4008TAG2A	HCI 634J	LSA 50.2 S3	
DP1000S	1250	1000	1375	1100	4012-46TWG2A	LVI 634G	LSA 50.2 M6	
DP1080S	1350	1080	1485	1188	4012-46TAGA1	PI 734B	LSA 50.2 L7	
DP1200S	1500	1200	1650	1320	4012-46TAG2A	PI 734C	LSA 50.2 L8	
DP1360S	1700	1360	1870	1496	4012-46TAG3A	PI 734D	LSA 50.2 VL10	
DP1400S	1750	1400	1925	1540	4016TAG	PI 734E	LSA 51.2 S55	
DP1475S	1844	1475	2028	1622.5	4016TAG1A	PI 734E	LSA 51.2 S55	
DP1650S	2063	1650	2269	1815	4016TAG2A	PI 734F	LSA 51.2 M60	
DP1800S	2250	1800	2475	1980	4016-61TRG3A	PI 734G	LSA 51.2 VL85	

